

## 33 Series

# 303 Power Amplifier (production from 1967-1985)

### Features

- High quality stereo power amplifier.
- Designed to be used in conjunction with Quad control unit/pre-amplifiers.
- Adequate output power for normal installations.



### Specification

Controls	None
Input	500mV from control unit
Output	45w sine per channel into 8 ohms
Dimensions	120mm wide; 159mm high; 423mm deep
Weight	9.0Kg
Finish	Brown
Audio Sockets	4-pin DIN
Speaker Sockets	4mm banana (short reach)

### Main Accessories/Spares

Description	Spares ref.	
4-pin DIN to 4-pin DIN signal lead (1m)	QD4D41A	
4-pin DIN to Phono plugs signal lead (1m)	QD4FP1A	for control units with phono outputs
AC interconnect 2-pin to 3-pin Bulgin socket 1m	QU2ES1A	before s/no 80500
AC interconnect 2-pin to 3-pin Euro socket 1m	QU2BS1A	after s/no 80500
Loudspeaker plug 4mm (red)	PP378A2	short reach
Loudspeaker plug 4mm (black)	PP378A0	short reach
Capacitor 2200 uF 100V	C2K2UTA	
Capacitor fixing clip 41mm diameter	FCR1527	
Capacitor inverting kit	Q03CAPI	
Foot (usually 4 required)	AFCOL12	